#### Go to www.vtechphones.com

Parent unit overview

 $\overline{\mathcal{O}}$ 

+ / VOL / -

ወ

speaker volume.

turned on.

Microphone

micro SD card slot

∩ 3.5mm audio jack

Antenna

Speaker

RESET

🗄 USB jack

charging.

10

Press to increase or decrease the

Press to turn on or off the screen

display without powering off the

parent unit. You can still hear sound

from the camera unit if the camera

is streaming in Single View and the

speaker volume of the parent unit is

to reboot the parent unit.

5-inch touch screen monitor

Force reboot the parent unit.

Connect to stereo earphone.

Connect to a power supply for

<u>Press and hold</u> to power on or off, or

to register your product for enhanced warranty support and latest VTech product news.




## Wi-Fi Pan and Tilt HD Video Monitor

# (BC)

<u>Д</u>! 🗍 100% 10:35 АМ vtech

# 

How the system works The Wi-Fi router (not included) provides Internet connectivity to your HD video monitor system. It serves as a communicating channel between your camera unit and parent unit, allowing you to monitor and/or control your camera unit wherever you are.



#### Protect your privacy and online security

VTech cares about your privacy and peace of mind. That's why we've put together a list of industry-recommended best practices to help keep your wireless connection private and your devices protected when online. We recommend you carefully review and consider complying with the following tips.

• Before installing a device, ensure your router's wireless signal is encrypted by selecting the "WPA2-PSK with AES" setting in your router's wireless security menu.

Change default settings.

- Change your wireless router's default wireless network name (SSID) to something unique. Change default passwords to unique, strong

## Congratulations

on purchasing your new VTech product. Before using this HD video monitor, please read Important safety instructions. For support, shopping, and everything new at VTech, visit our website at www.vtechphones.com. In Canada, visit

#### Introduction

www.vtechcanada.com

VTech Wi-Fi HD Video Monitor allows you to stay close to your baby when you are on the move or away

This monitor is Wi-Fi enabled, which uses your home wireless network to stream live video and audio through the HD camera unit and 5-inch touch screen parent unit. It allows you to maintain a constant connection to your baby.


You can also monitor from your smartphone and mobile tablet

VTech Wi-Fi HD Video Monitor uses MyVTech Baby app to let you instantly see and hear what's happening with your baby from anywhere in the world.

The app can be downloaded from the App Store or the Google Play<sup>™</sup> Store, directly from your smartphone or mobile tablet.

#### What's in the box

Your HD video monitor package contains the following items. Save your sales receipt and original packaging in the event warranty service is necessary.











## Requirements

Make sure your system includes the following components, and they meet the minimum requirement.

Wi-Fi
2.4GHz IEEE 802.11 b/g/n
At least 1.0 Mbps upload bandwidth per camera
Support Class 4 or higher, with storage capacity up to 32GB
Connect up to 4 camera units
Connect up to 10 camera units

#### Connect

You can choose to set up the camera unit for desktop usage, wall mounting, or ceiling mounting.


#### 🖹 Notes


- Use only the power adapters supplied with this product. Make sure the parent unit and the camera unit are
- not connected to the switch controlled electric outlets
- Connect the power adapters in a vertical or floor mount position only. The adapters' prongs are not designed to hold the weight of the parent unit and the camera unit, so do not connect them to any ceiling, under-the-table, or cabinet outlets. Otherwise, the adapters may not properly connect to the outlets
- Make sure the parent unit, the camera unit and the power adapter cords are out of reach of children.


#### Connect the camera unit

### Wi-Fi connection


- Before you connect the camera unit, make sure you
- have Internet access and a Wi-Fi router (IEEE 802.11 b/g/n). Charges apply and service plan may vary for Internet access. Router is not included
- Do not plug in the network cable. • To maintain compliance with the FCC's RF exposure
- guidelines, place the camera unit at least 20cm from nearby persons.














- 🖹 Note


















vtech

Overview

(2)





------

- Is complex.
- personal information.
- Contains a mix of uppercase letters, lowercase letters, special characters and numbers.

Keep your devices up to date.

- Download security patches from manufacturers as soon as they become available. This will ensure you always have the latest security updates.
- If the feature is available, enable automatic updates for future releases.

Disable Universal Plug and Play (UPnP) on your router.

UPnP enabled on a router can limit the effectiveness of your firewall by allowing other network devices to open inbound ports without any intervention or approval from you. A virus or other malware program could use this function to compromise security for the entire network.

For more information on wireless connections and protecting your data, please review the following resources from industry experts:

1. Federal Communications Commission: Wireless Connections and Bluetooth Security Tips -

www.fcc.gov/consumers/guides/howprotect-yourself-online.

- 2. U.S. Department of Homeland Security: Before You Connect a New Computer to the Internet – www.us-cert.gov/ncas/tips/ST15-003.
- 3. Federal Trade Commission: Using IP Cameras Safely -

https://www.consumer.ftc.gov/articles/0382using-ip-cameras-safely.

4. Wi-Fi Alliance: Discover Wi-Fi Security -



WÎFi Ś


Ensure your wireless connection is secure.

- passwords. A strong password:
- Is at least 10 characters long.


# Installation guide

- - Does not contain dictionary words or





1. Connect the power adapter to the camera unit and a power supply.




2. Place the camera unit at a desired place.

To turn off the camera unit, unplug the camera unit from the power supply.


#### **Cable connection (optional)**

After you have paired the camera unit with your parent unit via Wi-Fi, you can connect the camera unit to the Internet using the network cable to optimize your Internet connection.



Read the following Set up the HD video monitor section to set up your parent unit and pair your

1	Light concor		
1	Light sensor		
2	<ul> <li>Infrared LEDs</li> <li>Allow you to see clearly in a dark surrounding.</li> </ul>		
3	Camera lens		
4	Microphone		
5	<ul><li>Antenna</li><li>Connect to router with Wi-Fi.</li></ul>		
6	Speaker		
7	Power jack		
8	<ul> <li>Ethernet port</li> <li>Connect to router with an RJ45 network cable (optional).</li> </ul>		
9	<ul> <li>3.5mm line jack</li> <li>Connect to audio output device (optional).</li> </ul>		
10	micro SD card slot		
11	<ul> <li>LED indicators</li> <li>Flash orange and blue alternately when the camera unit is in pairing mode.</li> <li>Orange is steady on when the camera unit is connecting to the Internet.</li> <li>Orange and blue are steady on when the camera unit is idle.</li> <li>Flash orange and blue slowly during video streaming.</li> <li>Flash orange and blue quickly and alternately when the camera unit is updating its firmware.</li> <li>☆: TIP</li> <li>You can turn off the camera unit's LEDs if you find them too bright. Read the LED online indicator section under Camera settings in your parent unit's app manual for instructions.</li> </ul>		
12	<ul> <li>Volume –</li> <li>Press to decrease the camera unit speaker volume.</li> <li>Volume +</li> <li>Press to increase the camera unit speaker volume.</li> </ul>		
13	<ul> <li>Pair/reset button</li> <li>Press and hold for four seconds to enter pairing mode.</li> </ul>		



#### Charge before use

#### 🖹 Notes

- Charge the parent unit before use. The parent unit is fully charged after 2.5 hours of continuous charging
- It takes longer to charge when the parent unit is turned on. To shorten the charging time, turn the parent unit off while charging.
- The standby time varies depending on your actual

After the parent unit is fully charged, press and hold 0 to power on.



The battery icon indicates the battery status (see the following table).

Battery indicators	Battery status	Αςτιόν
The screen displays 🗐.	The battery has very little charge and may be used for only a short time.	Charge without interruption (about 30 minutes).
The battery icon becomes solid .	The battery is fully charged.	To keep the battery charged, connect it to AC power when not in use.

#### Insert micro SD card

#### Insert micro SD card into the camera unit (recommended)


Your camera unit can capture videos of the monitoring area when motion is detected. You can choose to save the videos to a micro SD card (purchased separately).

#### NOTE 1

Your camera unit supports Class 4 or higher micro SD card, with storage capacity up to 32GB.

#### **()** CAUTION

Prior to inserting or ejecting the micro SD card, the camera unit must be powered off. To power off, unplug the camera from the power supply.




2. Adjust the angle of the camera to aim at your baby. Refer to the online app manual on how to use the Pan/tilt and Zoom functions of the camera



#### 尜TiP

- Increase the parent unit speaker volume if you cannot hear the sounds transmitted from the camera unit when the Play sound function is enabled
- 3. To avoid causing high-pitched screeching noise from your HD video monitor when the Play sound or Two-way talk function of the camera unit is enabled:
- Make sure your camera unit and parent unit are more than 1 meter (3 feet) apart; OR
- Turn down the volume of your parent unit.



#### Pair new camera unit

You can add or replace any camera units to your HD video monitor system.


The HD video monitoring family includes VM981 and VM991. Their respective camera units are VM980 and VM990, which can be purchased separately. They can be cross-paired within the family, for example, you can have a combination of VM991 and VM980. You can pair a maximum of 4 camera units to your parent unit.

For more details, refer to the user's manual of your new camera unit (VM980 or VM990). You Insert micro SD card into the parent unit (recommended)

You can insert a micro SD card (purchased separately) into the parent unit for storing the snapshots taken and videos recorded manually with your camera unit.

🖹 Note

To get the snapshots and videos stored in the micro SD card, you need to remove the SD card from your parent unit, and then insert it into another device. such as a smartphone, tablet or card reader and copy the snapshots and videos.



#### Set up the HD video monitor

After you have connected the parent unit and the camera unit, refer to the Quick start guide included in your package to set up your HD video monitor system.

HD video monitor setup:

 Set up Wi-Fi connection Add camera

#### Test the location for the camera unit

Before vou install vour camera unit, vou need to test which of your selected monitoring areas within the house have good Wi-Fi signal strength. After you have connected your parent unit to a Wi-Fi network, you can use your parent unit's Wi-Fi signal strength indicator to assist in checking. Once you have identified the suitable location, vou can install vour camera unit. Adjust the distance between your camera unit and the Wi-Fi router if needed.

can also refer to the online installation guide and the app manual of your HD video monitor system (VM981 or VM991) in the Help page of your parent unit.

------

#### 🖹 Note

Your parent unit can pair and access a maximum of 4 camera units. You can add more camera units to your HD video monitor system using the MyVTech Baby mobile app. Download the mobile app and create a camera account. Then, you can use the mobile app to pair your existing camera units in your parent unit to your camera account, and also pair additional camera units to your account. The mobile app can pair and access up to 10 camera units. The additional camera units can only be paired and accessed via the mobile app.



Download the free MyVTech Baby app

#### General product care

To keep this product working well and looking good, follow these guidelines:


- Avoid putting it near heating appliances and devices that generate electrical noise (for example, motors or fluorescent lamps).
- DO NOT expose it to direct sunlight or moisture.
- Avoid dropping the product or treating it roughly.
- Clean with a soft cloth. DO NOT immerse the camera unit in water
- and do not clean it under the tap. • DO NOT use cleaning spray or liquid cleaners. • Make sure the parent unit and camera unit are dry before you connect them to the mains

#### Storage

again

When you are not going to use the HD video monitor for some time, store the parent unit, the camera unit, and the adapters in a cool and dry place.


- 崇TiP
  - Depending on surroundings and obstructing factors, such as the effect distance and internal walls have on signal strength, you may experience reduced Wi-Fi signal. To improve the Wi-Fi signal strength, adjust the distance or direction of your



#### Mount the camera unit (optional)

#### 🖹 Note

- The types of screws and anchors you need depend on the composition of the wall. You may need to purchase the screws and anchors separately to mount your camera units.
- Place the wall mount bracket on a wall or on the ceiling, and then use a pencil to mark two holes in parallel.



- 2. Remove the wall mount bracket and then drill two holes in the wall or on the ceiling (7/32" drill bit).
  - If you drill the holes into an object other than a stud, insert the wall anchors into the holes and tap gently on the ends with a hammer until the wall anchors are flush with the wall

#### Frequently asked questions

Below are the questions most frequently asked about the HD video monitor. If you cannot find the answer to your question in the below table, visit our website at www.vtechphones.com or call 1-844-848-8324 (1-844-84-VTECH) for customer service. In Canada, go to

www.vtechcanada.com or call 1-888-211-2005. Can I turn off Press 🕐 to turn off the screen


the parent unit screen but keep hearing sound from the camera unit?	display without powering off the parent unit. You can still hear sound from the camera unit if the camera is streaming in Single View and the speaker volume of the parent unit is turned on.
The LEDs on the camera unit are too bright. Can I turn them off?	You can turn off the LEDs of your camera units. Read the <b>LED online indicator</b> section under <b>Camera settings</b> in your parent unit's app manual for instructions.
Why does the camera unit not respond normally?	<ul> <li>Try the following (in the order listed) for common cure:</li> <li>1. Disconnect the power to the camera unit.</li> <li>2. Wait a few minutes before connecting power back to the camera unit.</li> <li>3. Reboot the parent unit.</li> </ul>
Why is my screen in black and white?	The camera unit has a light sensor that measures the ambient light. When the ambient light is dim, such as during nighttime or in a dark room, the camera activates its infrared LEDs, and displays the camera view in black and white.
Why does my camera show offline?	The camera unit may lose the Internet connection. Check your network and the router setting.
Why is the connection lost every now and then?	Other electronic products may cause interference with your camera. Try installing your camera as far away from these electronic devices as possible.

### Limited warranty


#### What does this limited warranty cover?


The manufacturer of this VTech Product warrants to the holder of a valid proof of purchase ("Consumer" or "vou") that the Product and all accessories provided in

3. Align the holes on the wall mount bracket with the screws on the wall or on the ceiling. Tighten the screws in the holes.



4. Place the camera unit on the wall mount bracket, and then slide it forward until it locks into place.





the sales package ("Product") are free from defects in material and workmanship, pursuant to the following terms and conditions, when installed and used normally and in accordance with the Product operating instructions. This limited warranty extends only to the Consumer for Products purchased and used in the United States of America and Canada

#### What will VTech do if the Product is not free from defects in materials and workmanship during the limited warranty period ("Materially Defective Product")?

During the limited warranty period, VTech's authorized service representative will repair or replace at VTech's option, without charge, a Materially Defective Product. If we repair the Product, we may use new or refurbished replacement parts. If we choose to replace the Product, we may replace it with a new or refurbished Product of the same or similar design. We will retain defective parts, modules, or equipment Repair or replacement of the Product, at VTech's option, is your exclusive remedy. VTech will return the repaired or replacement Products to you in working condition. You should expect the repair or replacement to take approximately 30 days

#### How long is the limited warranty period?

The limited warranty period for the Product extends for ONE (1) YEAR from the date of purchase. If VTech repairs or replaces a Materially Defective Product under the terms of this limited warranty, this limited warranty also applies to the repaired or replacement Product for a period of either (a) 90 days from the date the repaired or replacement Product is shipped to you or (b) the time remaining on the original one-year warranty; whichever is longer.

#### What is not covered by this limited warranty?

This limited warranty does not cover:

5.

7.

- 1. Product that has been subjected to misuse, accident, shipping or other physical damage, improper installation, abnormal operation or handling, neglect, inundation, fire, water or other liquid intrusion; or
- 2. Product that has been damaged due to repair, alteration or modification by anyone other than an authorized service representative of VTech; or
- 3. Product to the extent that the problem experienced is caused by signal conditions, network reliability, or cable or antenna systems; or 4. Product to the extent that the problem is caused by
- use with non-VTech accessories; or
- Product whose warranty/quality stickers, product serial number plates or electronic serial numbers have been removed, altered or rendered illegible;
- 6. Product purchased, used, serviced, or shipped for repair from outside the United States of America or Canada, or used for commercial or institutional purposes (including but not limited to Products used for rental purposes); or
- Product returned without a valid proof of purchase (see item 2 on the next column); or

wall switch.



## (optional)









warrantv

5. Connect the power adapter to the camera unit and a power supply not controlled by a



# Connect to audio output device

The camera unit has a built-in speaker. You can also connect an external self-powered speaker to your camera unit for extra sound quality.



8. Charges for installation or set up, adjustment of customer controls, and installation or repair of systems outside the unit

#### How do you get warranty service?

To obtain warranty service in the USA, please visit our website at www.vtechphones.com or call 1-844-848-8324 (1-844-84-VTECH). In Canada, go to www.vtechcanada.com or call 1-888-211-2005

NOTE: Before calling for service, please review the user's manual - a check of the Product's controls and features may save you a service call

Except as provided by applicable law, you assume the risk of loss or damage during transit and transportation and are responsible for delivery or handling charges incurred in the transport of the Product(s) to the service location. VTech will return repaired or replaced Product under this limited warranty. Transportation, delivery or handling charges are prepaid. VTech assumes no risk for damage or loss of the Product in transit. If the Product failure is not covered by this limited warranty, or proof of purchase does not meet the terms of this limited warranty, VTech will notify you and will request that you authorize the cost of repair prior to any further repair activity. You must pay for the cost of repair and return shipping costs for the repair of Products that are not covered by this limited

#### What must you return with the Product to get warranty service?

1. Return the entire original package and contents including the Product to the VTech service location along with a description of the malfunction or difficulty; and

2. Include a "valid proof of purchase" (sales receipt) identifying the Product purchased (Product model) and the date of purchase or receipt; and

3. Provide your name, complete and correct mailing address, and telephone number.

#### **Other limitations**

This warranty is the complete and exclusive agreement between you and VTech. It supersedes all other written or oral communications related to this Product. VTech provides no other warranties for this Product. The warranty exclusively describes all of VTech's responsibilities regarding the Product. There are no other express warranties. No one is authorized to make

modifications to this limited warranty and you should not rely on any such modification. State/Provincial Law Rights: This warranty gives you specific legal rights, and you may also have other rights, which vary

from state to state or province to province. Limitations: Implied warranties, including those of fitness for a particular purpose and merchantability (an unwritten warranty that the Product is fit for ordinary use) are limited to one year from the date of purchase. Some states/provinces do not allow limitations on how long an implied warranty lasts, so the above limitation may not apply to you. In no event shall VTech be liable for

#### Before use

#### 🖹 Note

· This HD video monitor is intended as an aid. It is not a substitute for proper adult supervision, and should not be used as such.

#### Testing the sound level of the HD video monitor

#### **OCAUTION**


For hearing protection, make sure the parent unit is more than 1 meter (3 feet) away from the camera unit. If you hear any high-pitched noise from the parent unit when the Play sound or Two-way talk function of the camera unit is enabled, move the parent unit further until the noise



stops. You can also press -/VOL on the parent unit to lower or mute the noise.

#### 尝TiP

Increase the parent unit speaker volume if you cannot hear the sounds transmitted from the camera unit when the Play sound function is enabled.




#### Positioning the HD video monitor

#### () CAUTION

Keep the camera unit out of the reach of your baby. Never place or mount the camera unit inside the baby's crib or playpen.

1. Place the camera unit more than 1 meter (3 feet) away from your baby.



any indirect, special, incidental, consequential, or similar damages (including, but not limited to lost profits or revenue, inability to use the Product or other associated equipment, the cost of substitute equipment, and claims by third parties) resulting from the use of this Product. Some states/provinces do not allow the exclusion or limitation of incidental or consequential damages, so the above limitation or exclusion may not apply to you. Please retain your original sales receipt as proof of

## **Technical specifications**

purchase

Frequency	Camera unit: 2412 - 2462 MHz	
Channels	11	
LCD	5" Color LCD (IPS 480x854 pixels)	
Nominal effective range	Maximum power allowed by FCC and IC. Actual operating range may vary according to environmental conditions at the time of use.	
Power requirement	<ol> <li>Parent unit power adapter: Output: 5V DC 1.2A</li> <li>Parent unit: 3.7V Li-polymer battery is built-in.</li> </ol>	
	Camera unit power adapter: Output: 5V DC 1500mA	

Google Play and the Google Play logo are trademarks of Google LLC

App Store is a trademark of Apple Inc., registered in the U.S. and other countries





Specifications are subject to change without notice 🖻 2018 VTech Communications, Inc All rights reserved. 08/18. VM991\_IG\_V8.0 Document order number: 91-011404-010-100